

**Acue<sup>®</sup>Lighting**

PROFESSIONAL STAGE LIGHTING



***Pixel 18***  
***MaTrix Bar***

**Product User Guide**

## 1,Digital display

display	Mode	Function
<b>Addr</b>	DMX address setting And Channel mode	A001-A512/3CH B001-B512/5CH C001-C512/7CH D001-D512/54CH E001-D512/9CH F001-D512/15CH
<b>rL--</b>	Red	r000-255
<b>gL--</b>	Green	g000-255
<b>bL--</b>	Blue	b000-255
<b>FLAS</b>	Shut	FL00
<b>FAdE</b>	Fade	FA00
<b>ASC-</b>	Color Macro	AS00
<b>CE--</b>	Program	CE00
<b>CS--</b>	Program Speed	CS00
<b>SLNd</b>	Slave mode	From the machine
<b>SHNd</b>	Show mode	6 color jump
<b>SOUN</b>	Sound mode	Voice
<b>SENE</b>	Sound sense	Acoustic sensitivity

## 2,DMX operation

### 3CH mode:A

CH1	0-255	Red
CH2	0-255	Green
CH3	0-255	Blue

### 5CH Mode:B

CH1	0-255	Red
CH2	0-255	Green
CH3	0-255	Blue
CH4	0-255	no
CH5	0-255	Dimmer

### 7CH Mode:C

CH1	0-255	Red
CH2	0-255	Green
CH3	0-255	Blue
CH4	0-255	CTO
CH5	0-255	Strobe

CH6	0-255	Macro
CH7	0-255	Dimmer

**54CH Mode:D**

CH1	0-255	Red
CH2	0-255	Green
CH3	0-255	Blue
.....	.....	.....
CH54	0-255	Blue

**9CH Mode:E**

CH1	0-255	Red
CH2	0-255	Green
CH3	0-255	Blue
.....	.....	.....
CH9	0-255	Blue

**15CH Mode:F**

CH1	0-255	Red
CH2	0-255	Green
CH3	0-255	Blue
CH4	0-255	Dimmer
CH5	0-255	Strobe
.....	.....	.....
CH15	0-255	Strobe

**Safety instruction**

**!CAUTION HIGH VOLTAGE!**

Always check wires for damages. Make sure there are no bare wires visible. Be sure to discard damaged wires. Do not use in wet or humid conditions.

For more information you can contact us at [Info@Acuelighting.com](mailto:Info@Acuelighting.com) or visit our website [www.AcueExpress.com](http://www.AcueExpress.com)

Voltage: AC100-240V 50/60Hz

Maximum Power Draw: 200W

Light source: 18pcs 9W RGB 3in1 LEDs

Channel Modes: 3,5,7,54,9,15

Sound controllable via built-in microphone

Adjustable sound sensitivity

Function: Color mix, automatic color change, built-in program and strobe effect with adjustable speed, dimmer, master/slave

LED display, easy to control

Control: Auto, sound active, DMX512, software (connect to computer)

Full DMX512 control

Safety: Safety cable mounting point included

Size: 100x6.5xCM

Weight: 5.3kg